

FlexMove®


FG
Conveyor Guide Rail



FG SERIES


FGDT-70	Distance Tube, L = 70mm - Aluminium
FGDT-80	Distance Tube, L = 80mm - Aluminium
FGDT-100	Distance Tube, L = 100mm - Aluminium
FGDT-150	Distance Tube, L = 150mm - Aluminium
FGDT-200	Distance Tube, L = 200mm - Aluminium
FGDT-250	Distance Tube, L = 250mm - Aluminium






UOM : 10 pcs / pk


FGGR-18X100	18mm Tube, L = 100mm - Aluminium
FGGR-18X150	18mm Tube, L = 150mm - Aluminium
FGGR-18X200	18mm Tube, L = 200mm - Aluminium
FGGR-18X250	18mm Tube, L = 250mm - Aluminium
FGGR-18X300	18mm Tube, L = 300mm - Aluminium






UOM : 10 pcs / pk

FGEC-18 — End cap. 18mm Tube - Polyamide



UOM : 10 pcs / pk


FGEC-20 — End cap , Distance Tube - Polyamide



UOM : 10 pcs / pk


FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.

FGAP-25 Spring Pin - Steel



UOM: 50pcs / pk


FGRA-26x39x45A Bracket for sensor - Aluminium



UOM : 10 pcs / pk

FGRA-8x39x45 Adjustable Guide Rail Bracket - Aluminium

Including Spring pin, M6 screw & Nut




UOM : 10 pcs / pk

Mounting to beam : FATB-20 (1) , FALN-M8 (1) , FAFW-M8 (1)

FGRA-8x9x45 Adjustable Guide Rail Bracket - Aluminium

Including Spring pin, M6 screw & Nut





UOM : 10 pcs / pk

Mounting to beam : FATB-20 (1) , FALN-M8 (1) , FAFW-M8 (1)

FGRA-26x39x45 — Adjustable Guide Rail Bracket - Aluminium

Including Spring pin, M8 screw & nut







UOM : 10 pcs / pk

Mounting to beam : FATB-20 (1) , FALN-M8 (1) , FAFW-M8 (1)

FGRA-26x9x45 — Adjustable Guide Rail Bracket - Aluminium

Including Spring pin, M8 screw & nut






UOM : 10 pcs / pk

Mounting to beam : FATB-20 (1) , FALN-M8 (1) , FAFW-M8 (1)

FGRB-16x54 — Fixed Guide Rail Bracket - Aluminium

Including Spring pin.






UOM : 10 pcs / pk


Mounting to beam : FATB-20 (1) , FALN-M8 (1) , FAFW-M8 (1)

FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.

FGRB-16x42 — Fixed Guide Rail Bracket - Aluminium

Including Spring pin.






UOM : 10 pcs / pk

Mounting to beam : FATB-20 (1) , FALN-M8 (1) , FAFW-M8 (1)

FGRB-28x42 — Fixed Guide Rail Bracket - Aluminium

Including Spring pin.







UOM : 10 pcs / pk

Mounting to beam : FATB-20 (1) , FALN-M8 (1) , FAFW-M8 (1)

FGRB-40x42 — Fixed Guide Rail Bracket - Aluminium

Including Spring pin.







UOM : 10 pcs / pk

Mounting to beam : FATB-20 (1) , FALN-M8 (1) , FAFW-M8 (1)

FGRB-49x42 — Fixed Guide Rail Bracket - Aluminium

Including Spring pin.







UOM : 10 pcs / pk

Mounting to beam : FATB-20 (1) , FALN-M8 (1) , FAFW-M8 (1)

FGRB-53x42 — Fixed Guide Rail Bracket - Aluminium

Including Spring pin.







UOM : 10 pcs / pk

Mounting to beam : FATB-20 (1) , FALN-M8 (1) , FAFW-M8 (1)

FGRB-90x42 — Fixed Guide Rail Bracket - Aluminium

Including Spring pin.







UOM : 10 pcs / pk


Mounting to beam : FATB-20 (1) , FALN-M8 (1) , FAFW-M8 (1)

FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.

FGRD-6 Guide Rail Bracket Spacer - Aluminium










UOM : 10 pcs / pk


FGRC-20 Guide Rail Support - Aluminium

Including Spring pin.











UOM : 10 pcs / pk


Mounting : FAHB-M8 x 12 (1) , FASN-M8 (1) , FAFW-M8 (1)

FGRC-20A Guide Rail Support - Aluminium

Including Spring pin.









UOM : 10 pcs / pk

Mounting: C'SUNK M8 x 12


FGRR-15x20 Guide Rail Rectangular, 15mm x 20mm - Aluminium






UOM: 3meter / length


FGRR-10x20 Guide Rail Rectangular, 10mm x 20mm - Aluminium






UOM: 3meter / length

FGRR-10x20F Guide Rail Rectangular, 10mm x 20mm Type F - Aluminium







UOM: 3meter / length

FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.

FGRR-15X20P — Guide Rail Rectangular, 15mm x 20mm – HDPE







UOM: 3meter / length

FGRT-3x23 — Guide Rail Cover - HDPE


FGRT-3x23A — Guide Rail Cover – HDPE (Conductive)






UOM: 3meter / length


FGRT-3x33 — Guide Rail Cover - HDPE






UOM: 3meter / length


FGRR-15x40 — Guide Rail Rectangular, 15mm x 40mm – Aluminium





UOM: 3meter / length

FGEC-15x40 — End Cap for FGRR-15x40 - Polyamide











UOM: 10pcs / pk

FGVG-3 — Special V Guide - Aluminium






UOM: 3meter / length

FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.

FGEC-15x20

End Cap for FGRR-15x20 - Polyamide




UOM: 10pcs / pk

FGRC-100

Rail Connecting – Aluminium L = 100mm , B = 50mm

FGRC-60


Rail Connecting – Aluminium L = 60mm , B = 30mm



UOM: 10pcs / pk


FGEC-10x20

End Cap for FGRR-10x20 & FGRR10x20F - Polyamide




UOM: 10pcs / pk

FGRJ-15x20 — Connecting Plug for FGRR-15x20 - Polyamide




UOM: 10pcs / pk

FGRJ-10x20 — Connecting Plug for FGRR-10x20 & FGRR-10x20F - Polyamide



UOM: 10pcs / pk

FGEC-30D — 30° End Cap for FGRR-15x20 - Polyamide





UOM: 3meter / length

FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.

FGRS-18 Guide Rail Support - Polyamide










UOM: 10pcs / pk

FGRS-15x20 Guide Rail Support - Polyamide









UOM: 10pcs / pk


FGRS-18F — Guide Rail Support - Polyamide












UOM: 10pcs / pk

FGRL-18x110C — Guide Rail Support, L = 110mm - Polyamide

FGRL-18x160C — Guide Rail Support, L = 160mm - Polyamide








UOM: 10pcs / pk


To be used directly with guide rail bracket support FGRF- 42 x 18V or FGRB-18 x 20


FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.

FGRC-18x110C
Double Guide Rail Support, L = 110mm - Polyamide

FGRC-18x160C
Double Guide Rail Support, L = 160mm - Polyamide







UOM: 10pcs / pk

Suitable for use with cross connector FGRB-18 x18 and a crossing 18 mm aluminum tube above the double track.

FGRK-18x40A
Guide Rail Support, L = 40mm - Polyamide


FGRK-18x60A
Guide Rail Support, L = 60mm - Polyamide


FGRK-18x80A
Guide Rail Support, L = 80mm - Polyamide

FGRK-18x130A
Guide Rail Support, L = 130mm - Polyamide









UOM: 10pcs / pk

Suitable for use with cross connector FGRB-18 x18 and FGRF – 42 x 18V

FGRL-18x110CA

Guide Rail Support, L = 110mm - Polyamide

FGRL-18x160CA

Guide Rail Support, L = 160mm - Polyamide



UOM: 10pcs / pk

Suitable for use with cross connector FGRK – 18 x 80 / 130 / 40A / 60A / 80A /130A




FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.

FGRF-42x18V

Guide Rail Bracket – Polyamide










UOM: 10pcs / pk

To be used with :

- FGGR - 18 x * 100
- FGRL - 18 x 110C / 160C
- FGRC - 18 x 110C / 160C




For use with guide rail bracket support FGRF -42 x 18V



FGRD-18A


Spacer for FGRF-42x18V - Polyamide



UOM: 10pcs / pk

FGRD-6A


Spacer for FGRF-42x18V - Polyamide



UOM: 10pcs / pk


FGRD-6C

Spacer for FGRF-42x18V - Polyamide



UOM: 10pcs / pk


FGRF-A35 Guide Rail Bracket A35 – Polyamide



UOM: 10pcs / pk

To be used with guide rail support . For 1-2 guide rail levels.


FGRF-A110 Guide Rail Bracket A110 – Polyamide




UOM: 10pcs / pk


To be used with guide rail support . For 1-4 guide rail levels.

FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.



FGRB-40x18	Guide Rail Bracket, D = 18mm - Polyamide
FGRB-40x20	Guide Rail Bracket, D = 20mm - Polyamide






UOM: 10pcs / pk




FGRB-40x15x20 Guide Rail Bracket - Polyamide






UOM: 10pcs / pk


FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.



FGRD-6B

Spacer for FGRB-40x # # - Polyamide







UOM: 10pcs / pk

For use with guide rail bracket support :
FGRB – 40 x 18 / 20
FGRB – 40 x 15 x 20


FGRB-18x18	Guide Rail Bracket, ØA = 18mm, ØB = 18mm - Polyamide
FGRB-18x20	Guide Rail Bracket, ØA = 18mm, ØB = 20mm - Polyamide
FGRB-20x20	Guide Rail Bracket, ØA = 20mm, ØB = 20mm - Polyamide






UOM: 10pcs / pk

FGRB-18x20T	Guide Rail Bracket, ØA = 18mm - Polyamide
FGRB-20x20T	Guide Rail Bracket, ØA = 20mm - Polyamide






UOM: 10pcs / pk

FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.

FGRX-18X20 — 90° Corner Connector - Polyamide






UOM: 10pcs / pk

For use with : FGGR – 18 x 100 / 150 / 200 / 250 / 300
FGDT – 70 / 80 / 100 / 150 / 200 250

FGRX-18x18 — 90° Corner Connector, ØA = 18mm, ØB = 18mm - Polyamide

FGRX-20x20 — 90° Corner Connector, ØA = 20mm, ØB = 20mm - Polyamide






UOM: 10pcs / pk

For use with : FGGR – 18 x 100 / 150 / 200 / 250 / 300
FGDT – 70 / 80 / 100 / 150 / 200 250

FGRX-15x20 — 90° Corner Connector - Polyamide







UOM: 10pcs / pk

For use with : FGRR – 15 x 20 / 20 P


FGSP-DT — Distance Tube Spacer - POM





UOM: 10pcs / pk

FGRB-16x54 — Fixed Guide Rail Assembly




B Spacer = FGRD-6

Guide Rail Bracket	Series	D (mm)	H (mm)	W (mm) B = 0	W (mm) B = 6.3	W (mm) B = 12.6	W (mm) B = 18.9
FGRB-16X54	FK	45	26	41.7	54.3	66.9	79.5
FGRB-16X54	FS	65	26	61.7	74.3	86.9	99.5
FGRB-16X54	FM	85	20	81.7	94.3	106.9	119.5
FGRB-16X54	FC	105	20	101.7	114.3	126.9	139.5
FGRB-16X54	FL	150	20	146.7	159.3	171.9	184.5

FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.


FGRB-16x42 Fixed Guide Rail Assembly



B Spacer = FGRD-6

Guide Rail Bracket	Series	D (mm)	H (mm)	W (mm) B = 0	W (mm) B = 6.3	W (mm) B = 12.6	W (mm) B = 18.9
FGRB-16X42	FK	45	14	41.7	54.3	66.9	79.5
FGRB-16X42	FS	65	14	61.7	74.3	86.9	99.5
FGRB-16X42	FM	85	8	-	94.3	106.9	119.5
FGRB-16X42	FC	105	8	-	114.3	126.9	139.5
FGRB-16X42	FL	150	8	-	159.3	171.9	184.5

FGRB-28x42 Fixed Guide Rail Assembly




B Spacer = FGRD-6

Guide Rail Bracket	Series	D (mm)	H (mm)	W (mm) B = 0	W (mm) B = 6.3	W (mm) B = 12.6	W (mm) B = 18.9
FGRB-28X42	FK	45	14	65.8	78.4	91	103.6
FGRB-28X42	FS	65	14	85.8	98.4	111	123.6
FGRB-28X42	FM	85	8	105.8	118.4	131	143.6
FGRB-28X42	FC	105	8	125.8	138.4	151	163.6
FGRB-28X42	FL	150	8	170.8	183.4	196	208.6

FGRB-40x42

Fixed Guide Rail Assembly




B Spacer = FGRD-6

Guide Rail Bracket	Series	D (mm)	H (mm)	W (mm) B = 0	W (mm) B = 6.3	W (mm) B = 12.6	W (mm) B = 18.9
FGRB-40X42	FK	45	14	90.6	103.2	115.8	128.4
FGRB-40X42	FS	65	14	110.6	123.2	135.8	148.4
FGRB-40X42	FM	85	8	130.6	143.2	155.8	168.4
FGRB-40X42	FC	105	8	150.6	163.2	175.8	188.4
FGRB-40X42	FL	150	8	195.6	163.2	220.8	233.4

FGRB-49x42

Fixed Guide Rail Assembly




B Spacer = FGRD-6

Guide Rail Bracket	Series	D (mm)	H (mm)	W (mm) B = 0	W (mm) B = 6.3	W (mm) B = 12.6	W (mm) B = 18.9
FGRB-49X42	FK	45	14	107.8	120.4	133	145.6
FGRB-49X42	FS	65	14	127.8	140.4	153	165.6
FGRB-49X42	FM	85	8	147.8	160.4	173	185.6
FGRB-49X42	FC	105	8	167.8	180.4	193	205.6
FGRB-49X42	FL	150	8	212.8	225.4	238	250.6

FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.


FGRB-53x42 Fixed Guide Rail Assembly



B Spacer = FGRD-6

Guide Rail Bracket	Series	D (mm)	H (mm)	W (mm) B = 0	W (mm) B = 6.3	W (mm) B = 12.6	W (mm) B = 18.9
FGRB-53X42	FK	45	14	115.7	128.3	140.9	153.5
FGRB-53X42	FS	65	14	135.7	148.3	160.9	173.5
FGRB-53X42	FM	85	8	155.7	168.3	180.9	193.5
FGRB-53X42	FC	105	8	175.7	188.3	200.9	213.5
FGRB-53X42	FL	150	8	220.7	233.3	245.9	258.5

FGRB-90x42 Fixed Guide Rail Assembly




B Spacer = FGRD-6

Guide Rail Bracket	Series	D (mm)	H (mm)	W (mm) B = 0	W (mm) B = 6.3	W (mm) B = 12.6	W (mm) B = 18.9
FGRB-90X42	FK	45	14	190.3	202.9	215.5	228.1
FGRB-90X42	FS	65	14	210.3	222.9	235.5	248.1
FGRB-90X42	FM	85	8	230.3	242.9	255.5	268.1
FGRB-90X42	FC	105	8	250.3	262.9	275.5	288.1
FGRB-90X42	FL	150	8	295.3	307.9	320.5	333.1

FGRB Mixed Guide Rail


Mixed Guide Rail Assembly



Guide Rail Bkt Left	C1 (mm)	Guide Rail Bkt Right	C2 (mm)	Series	D (mm)	H (mm)	W (mm) D + C1 + C2
FGRB-28x42	10.4	FGRB-40X42	22.8	FK	45	14	78.2
FGRB-28x42	10.4	FGRB-40X42	31.4	FK	45	14	86.8
FGRB-28x42	10.4	FGRB-53X42	35.3	FK	45	14	90.7
FGRB-28x42	10.4	FGRB-90X42	72.4	FK	45	14	127.8
FGRB-28x42	10.4	FGRB-40X42	22.8	FS	65	14	98.2
FGRB-28x42	10.4	FGRB-40X42	31.4	FS	65	14	106.8
FGRB-28x42	10.4	FGRB-53X42	35.3	FS	65	14	110.7
FGRB-28x42	10.4	FGRB-90X42	72.4	FS	65	14	147.8
FGRB-28x42	10.4	FGRB-40X42	22.8	FM	85	8	118.2
FGRB-28x42	10.4	FGRB-40X42	31.4	FM	85	8	126.8
FGRB-28x42	10.4	FGRB-53X42	35.3	FM	85	8	130.7
FGRB-28x42	10.4	FGRB-90X42	72.4	FM	85	8	167.8
FGRB-28x42	10.4	FGRB-40X42	22.8	FC	105	8	138.2
FGRB-28x42	10.4	FGRB-40X42	31.4	FC	105	8	146.8
FGRB-28x42	10.4	FGRB-53X42	35.3	FC	105	8	150.7
FGRB-28x42	10.4	FGRB-90X42	72.4	FC	105	8	187.8
FGRB-28x42	10.4	FGRB-40X42	22.8	FL	150	8	183.2
FGRB-28x42	10.4	FGRB-40X42	31.4	FL	150	8	191.8
FGRB-28x42	10.4	FGRB-53X42	35.3	FL	150	8	195.7
FGRB-28x42	10.4	FGRB-90X42	72.4	FL	150	8	232.8

FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.


FGRA-8x39x45 Adjustable Guide Rail Assembly



B Spacer = FGRD-6

Guide Rail Bracket	Series	D (mm)	H (mm)	W (mm) min B = 0	W (mm) max B = 0	W (mm) min B = 6.3	W (mm) max B = 6.3
FGRA-8x39x45	FK	45	17	0	12.2	0	24.8
FGRA-8x39x45	FS	65	17	0	32.2	0	44.8
Guide Rail Bracket	**Series**	**D (mm)**	**H (mm)**	**W (mm) min B = 12.6**	**W (mm) max B = 12.6**	**W (mm) min B = 18.9**	**W (mm) max B = 18.9**
FGRA-8x39x45	FM	85	11	86	90	86	102.6
FGRA-8x39x45	FC	105	11	106	110	106	122.6
FGRA-8x39x45	FL	150	11	156	155	156	167.6


FGRA-26x39x45 Adjustable Guide Rail Assembly



B Spacer = FGRD-6

Guide Rail Bracket	Series	D (mm)	H (mm)	W (mm) min B = 0	W (mm) max B = 0	W (mm) min B = 6.3	W (mm) max B = 6.3
FGRA-26x39x45	FK	45	24	28.8	100.8	41.4	113.4
FGRA-26x39x45	FS	65	24	48.8	120.8	61.4	133.4
FGRA-26x39x45	FM	85	18	68.8	140.8	81.4	153.4
FGRA-26x39x45	FC	105	18	88.8	160.8	101.4	173.4
FGRA-26x39x45	FL	150	18	133.8	205.8	146.4	218.4

FGRS-18 & FGDT- & FGRR- Guide Rail Assembly



A (mm)	Series	D (mm)	H (mm) Min	H (mm) Max
FGRR-100	FK	45	17	35
FGRR-100	FS	65	17	35
FGRR-100	FM	85	17	35
FGRR-100	FC	105	17	30
FGRR-100	FL	150	17	30

B (mm)	Series	D (mm)	W (mm) Min	W (mm) Max
FGDT-70	FK	45	0	65
FGDT-70	FS	65	0	85
FGDT-70	FM	85	16	105
FGDT-70	FC	105	36	125
FGDT-70	FL	150	81	170

A (mm)	Series	D (mm)	H (mm) Min	H (mm) Max
FGRR-150	FK	45	17	85
FGRR-150	FS	65	17	85
FGRR-150	FM	85	17	80
FGRR-150	FC	105	17	80
FGRR-150	FL	150	17	80

B (mm)	Series	D (mm)	W (mm) Min	W (mm) Max
FGDT-100	FK	45	0	125
FGDT-100	FS	65	0	145
FGDT-100	FM	85	16	165
FGDT-100	FC	105	36	185
FGDT-100	FL	150	81	230

A (mm)	Series	D (mm)	H (mm) Min	H (mm) Max
FGRR-200	FK	45	17	135
FGRR-200	FS	65	17	135
FGRR-200	FM	85	17	130
FGRR-200	FC	105	17	130
FGRR-200	FL	150	17	130


B (mm)	Series	D (mm)	W (mm) Min	W (mm) Max
FGDT-150	FK	45	0	225
FGDT-150	FS	65	0	245
FGDT-150	FM	85	16	265
FGDT-150	FC	105	36	285
FGDT-150	FL	150	81	330

A (mm)	Series	D (mm)	H (mm) Min	H (mm) Max
FGRR-250	FK	45	17	185
FGRR-250	FS	65	17	185
FGRR-250	FM	85	17	180
FGRR-250	FC	105	17	180
FGRR-250	FL	150	17	180

B (mm)	Series	D (mm)	W (mm) Min	W (mm) Max
FGDT-200	FK	45	0	325
FGDT-200	FS	65	0	345
FGDT-200	FM	85	16	365
FGDT-200	FC	105	36	385
FGDT-200	FL	150	81	430

FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.

FGRL-18x110C & FGDT-70
FGRL-18x110C & FGDT-100
FGRL-18x110C & FGDT-150
FGRL-18x110C & FGDT-200
FGRL-18x160C & FGDT-70
FGRL-18x160C & FGDT-100
FGRL-18x160C & FGDT-150
FGRL-18x160C & FGDT-200



Guide Rail Assembly

A (mm)	Series	D (mm)	H (mm) Min	H (mm) Max
FGRL-18x110C	FK	45	14	70
FGRL-18x110C	FS	65	14	70
FGRL-18x110C	FM	85	14	65
FGRL-18x110C	FC	105	14	65
FGRL-18x110C	FL	150	14	65

B (mm)	Series	D (mm)	W (mm) Min	W (mm) Max
FGDT-70	FK	45	23	110
FGDT-70	FS	65	43	130
FGDT-70	FM	85	63	150
FGDT-70	FC	105	83	170
FGDT-70	FL	150	128	215

A (mm)	Series	D (mm)	H (mm) Min	H (mm) Max
FGRL-18x160C	FK	45	14	120
FGRL-18x160C	FS	65	14	120
FGRL-18x160C	FM	85	14	115
FGRL-18x160C	FC	105	14	115
FGRL-18x160C	FL	150	14	115

B (mm)	Series	D (mm)	W (mm) Min	W (mm) Max
FGDT-100	FK	45	23	170
FGDT-100	FS	65	43	190
FGDT-100	FM	85	63	210
FGDT-100	FC	105	83	230
FGDT-100	FL	150	128	275



B (mm)	Series	D (mm)	W (mm) Min	W (mm) Max
FGDT-150	FK	45	23	270
FGDT-150	FS	65	43	290
FGDT-150	FM	85	63	310
FGDT-150	FC	105	83	330
FGDT-150	FL	150	128	375

B (mm)	Series	D (mm)	W (mm) Min	W (mm) Max
FGDT-200	FK	45	23	370
FGDT-200	FS	65	43	390
FGDT-200	FM	85	63	410
FGDT-200	FC	105	83	430
FGDT-200	FL	150	128	475

FGRL-18x110C & FGRK-18x80A

FGRL-18x110C & FGRK-18x80A

FGRL-18x110C & FGRK-18x80A


FGRL-18x110C & FGRK-18x80A

FGRL-18x160C & FGRK-18x80A

FGRL-18x160C & FGRK-18x80A

FGRL-18x160C & FGRK-18x80A

FGRL-18x160C & FGRK-18x80A



Guide Rail Assembly

A (mm)	Series	D (mm)	H (mm) Min	H (mm) Max
FGRL-18x110C	FK	45	14	70
FGRL-18x110C	FS	65	14	70
FGRL-18x110C	FM	85	14	65
FGRL-18x110C	FC	105	14	65
FGRL-18x110C	FL	150	14	65

B (mm)	Series	D (mm)	W (mm) Min	W (mm) Max
FGDT-70	FK	45	0	68
FGDT-70	FS	65	0	88
FGDT-70	FM	85	0	108
FGDT-70	FC	105	0	128
FGDT-70	FL	150	0	173

A (mm)	Series	D (mm)	H (mm) Min	H (mm) Max
FGRL-18x160C	FK	45	14	120
FGRL-18x160C	FS	65	14	120
FGRL-18x160C	FM	85	14	115
FGRL-18x160C	FC	105	14	115
FGRL-18x160C	FL	150	14	115

B (mm)	Series	D (mm)	W (mm) Min	W (mm) Max
FGDT-100	FK	45	0	128
FGDT-100	FS	65	0	148
FGDT-100	FM	85	0	168
FGDT-100	FC	105	0	188
FGDT-100	FL	150	0	233




B (mm)	Series	D (mm)	W (mm) Min	W (mm) Max
FGDT-150	FK	45	0	228
FGDT-150	FS	65	0	248
FGDT-150	FM	85	0	268
FGDT-150	FC	105	0	288
FGDT-150	FL	150	0	333

B (mm)	Series	D (mm)	W (mm) Min	W (mm) Max
FGDT-200	FK	45	0	328
FGDT-200	FS	65	0	348
FGDT-200	FM	85	0	368
FGDT-200	FC	105	0	388
FGDT-200	FL	150	0	433

FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.


FGRL-18x110C & FGRF-42x18V Guide Rail Assembly



B Spacer = FGRD-18A

Guide Rail	Guide Rail	Series	D (mm)	A (mm)	H (mm) Min	H (mm) Max	W (mm) B = 0	W (mm) B = 18	W (mm) B = 36
FGRL-18x110C	FGRF-42x18V	FK	45	110	3	75	71	107	143
FGRL-18x110C	FGRF-42x18V	FS	65	110	3	75	91	127	163
FGRL-18x110C	FGRF-42x18V	FM	85	110	3	70	111	147	183
FGRL-18x110C	FGRF-42x18V	FC	105	110	3	70	131	167	203
FGRL-18x110C	FGRF-42x18V	FL	150	110	3	70	176	212	248


FGRL-18x160C & FGRF-42X18V Guide Rail Assembly



B Spacer = FGRD-18A

Guide Rail	Guide Rail	Series	D (mm)	A (mm)	H (mm) Min	H (mm) Max	W (mm) B = 0	W (mm) B = 18	W (mm) B = 36
FGRL-18x160C	FGRF-42x18V	FK	45	160	3	135	71	107	143
FGRL-18x160C	FGRF-42x18V	FS	65	160	3	135	91	127	163
FGRL-18x160C	FGRF-42x18V	FM	85	160	3	130	111	147	183
FGRL-18x160C	FGRF-42x18V	FC	105	160	3	130	131	167	203
FGRL-18x160C	FGRF-42x18V	FL	150	160	3	130	176	212	248


FGRF-42x62-A110 & FGRK-18x80A — Guide Rail Assembly



B Spacer = FGRD-18A

Guide Rail	Guide Rail	Series	D (mm)	W min B = 0	W min B = 18	W min B = 36	W max B = 0	W max B = 18	W max B = 36
FGRF-42x62-A110	FGRK-18x80A	FK	45	0	3	39	61	97	133
FGRF-42x62-A110	FGRK-18x80A	FS	65	0	23	59	81	117	153
FGRF-42x62-A110	FGRK-18x80A	FM	85	7	43	79	101	137	173
FGRF-42x62-A110	FGRK-18x80A	FC	105	27	63	99	121	157	193
FGRF-42x62-A110	FGRK-18x80A	FL	150	72	108	144	166	202	238

FGRF-42x62-A35 & FGRK-18x80A — Guide Rail Assembly




B Spacer = FGRD-18A

Guide Rail	Guide Rail	Series	D (mm)	W min B = 0	W min B = 18	W min B = 36	W max B = 0	W max B = 18	W max B = 36
FGRF-42x62-A35	FGRK-18x80A	FK	45	0	3	39	61	97	133
FGRF-42x62-A35	FGRK-18x80A	FS	65	0	23	59	81	117	153
FGRF-42x62-A35	FGRK-18x80A	FM	85	7	43	79	101	137	173
FGRF-42x62-A35	FGRK-18x80A	FC	105	27	63	99	121	157	193
FGRF-42x62-A35	FGRK-18x80A	FL	150	72	108	144	166	202	238

FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.

FGRF-42x18V & FGRK-18x80A & FGRL18x110CA


FGRF-42x18V & FGRK-18x80A & FGRL18x160CA



B Spacer = FGRD-18A

Guide Rail	Series	D (mm)	A = 110 H (mm) Min	A = 110 H (mm) Max	A = 160 H (mm) Min	A = 160 H (mm) Max	B (mm)	W (mm) Min	W (mm) Max
FGRL-18x110C	FK	45	3	83	3	138	0	0	30
FGRL-18x110C	FS	65	3	83	3	138	0	0	50
FGRL-18x110C	FM	85	3	83	3	133	0	0	70
FGRL-18x110C	FC	105	3	83	3	133	0	0	90
FGRL-18x110C	FL	150	3	83	3	133	0	25	135
FGRL-18x110C	FK	45	3	83	3	138	18	0	78
FGRL-18x110C	FS	65	3	83	3	138	18	0	86
FGRL-18x110C	FM	85	3	83	3	133	18	0	106
FGRL-18x110C	FC	105	3	83	3	133	18	16	126
FGRL-18x110C	FL	150	3	83	3	133	18	61	171
FGRL-18x110C	FK	45	3	83	3	138	36	0	112
FGRL-18x110C	FS	65	3	83	3	138	36	12	132
FGRL-18x110C	FM	85	3	83	3	133	36	32	152
FGRL-18x110C	FC	105	3	83	3	133	36	52	172
FGRL-18x110C	FL	150	3	83	3	133	36	97	217
FGRL-18x110C	FK	45	3	83	3	138	54	28	148
FGRL-18x110C	FS	65	3	83	3	138	54	48	168
FGRL-18x110C	FM	85	3	83	3	133	54	68	188
FGRL-18x110C	FC	105	3	83	3	133	54	88	208
FGRL-18x110C	FL	150	3	83	3	133	54	133	243


FGRF-42x18V FGRS-18 & FGDT-150 Guide Rail Assembly



B Spacer = FGRD-18A

Guide Rail	Guide Rail	Series	D (mm)	A (mm)	H (mm) Min	H (mm) Max	W (mm) B = 0	W (mm) B = 18	W (mm) B = 36
FGRS-18	FGDT-150	FK	45	150	3	90	24	60	96
FGRS-18	FGDT-150	FS	65	150	3	90	44	80	116
FGRS-18	FGDT-150	FM	85	150	3	85	64	100	136
FGRS-18	FGDT-150	FC	105	150	3	85	84	120	156
FGRS-18	FGDT-150	FL	150	150	3	85	129	165	201

FGRF-42x18V FGRS-18 & FGDT-200 Guide Rail Assembly




B Spacer = FGRD-18A

Guide Rail	Guide Rail	Series	D (mm)	A (mm)	H (mm) Min	H (mm) Max	W (mm) B = 0	W (mm) B = 18	W (mm) B = 36
FGRS-18	FGDT-200	FK	45	200	3	140	24	60	96
FGRS-18	FGDT-200	FS	65	200	3	140	44	80	116
FGRS-18	FGDT-200	FM	85	200	3	135	64	100	136
FGRS-18	FGDT-200	FC	105	200	3	135	84	120	156
FGRS-18	FGDT-200	FL	150	200	3	135	129	165	201

FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.

FGRB-40x18 & FGRK-18x80 Guide Rail Assembly





B Spacer = FGRD-6B

Guide Rail	Guide Rail	Series	A (mm)	B (mm)	D (mm)	W (mm) Min	W (mm) Max
FGRB-40x18	FGRK-18x80	FK	80	0	45	0	55
FGRB-40x18	FGRK-18x80	FS	80	0	65	0	75
FGRB-40x18	FGRK-18x80	FM	80	0	85	0	95
FGRB-40x18	FGRK-18x80	FC	80	0	105	15	115
FGRB-40x18	FGRK-18x80	FL	80	0	150	60	160
FGRB-40x18	FGRK-18x80	FK	80	6	45	0	67
FGRB-40x18	FGRK-18x80	FS	80	6	65	0	87
FGRB-40x18	FGRK-18x80	FM	80	6	85	7	107
FGRB-40x18	FGRK-18x80	FC	80	6	105	27	127
FGRB-40x18	FGRK-18x80	FL	80	6	150	72	172
FGRB-40x18	FGRK-18x80	FK	80	12	45	0	79
FGRB-40x18	FGRK-18x80	FS	80	12	65	0	99
FGRB-40x18	FGRK-18x80	FM	80	12	85	19	119
FGRB-40x18	FGRK-18x80	FC	80	12	105	39	139
FGRB-40x18	FGRK-18x80	FL	80	12	150	84	184
FGRB-40x18	FGRK-18x80	FK	80	18	45	1	91
FGRB-40x18	FGRK-18x80	FS	80	18	65	21	111
FGRB-40x18	FGRK-18x80	FM	80	18	85	31	131
FGRB-40x18	FGRK-18x80	FC	80	18	105	51	151
FGRB-40x18	FGRK-18x80	FL	80	18	150	96	196

Bottling Guide Rail Assembly


Bottles Handling






Double Track Guide Rail Assembly

Cans Handling







FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.

Duo-Layer Guide Rail Assembly


Box Handling






Extra Bottom Guide Rail Assembly


Carton Box Handling






Width Adjustment Guide Rail Assembly


Packaging box Handling






Width Adjustment Guide Rail Assembly


Container Handling







FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.


Width & Height Adjustable Guide Rail Assembly — Box Handling







Width & Height Adjustable Guide Rail Assembly — Cans Handling






Width & Height Adjustable Guide Rail Assembly — Pucks Handling






Pallet Assembly line Guide Rail


Electronic Assembly Handling






Cassette Guide Rail Assembly


Disc Drive Cassette Handling






Width Adjustable Guide Rail Assembly

Box Handling






FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.

Width & Height Adjustable Guide Rail Assembly


Packaging Box Handling






Width & Height Guide Rail Assembly


Paper Converting Handling







Small Box Guide Rail Assembly

Small Box Handling







FGRB-16x42 Assembly




FGRB-28x42 Assembly




FGRB-40x42 Assembly




FGRB-49x42 Assembly



FGRB-53x42 Assembly




FGRB-90x42 Assembly




FlexMove reserves the right to make alteration without prior notification Every care has been taken to ensure the accuracy of the information contained in this catalogue but no liability can be accepted for any error or omissions.


FGRB-16x54 Assembly




Guide Rail Assembly



FGRA-26x39x45 Assembly



FGRA-6x9x45 Assembly



Twin Track Pallet Guide Rail Assembly

Pallet Handling

